

# WIRELESS DMX

INNLED®  
#madeinfrance

This new wireless transmitter provides all the same functionalities as its predecessor. Fitted with a colour LCD screen and a rotary knob, the navigation within the menu is now much simpler.

New modes automatically detect the available channels and avoid interferences.

The choice of the channels becomes elementary and your lamp is connected in a matter of minutes.



1. LCD screen  
WITH  
HF SNIFFER

2. 31 POSSIBLE  
UNIVERSES

3. 300M OPEN  
FIELD RANGE





Its LCD colour screen and its rotary knob ensure easier navigation within the menu and offer a better visibility on the frequencies.



The SCAN mode automatically detects the available channels and the frequencies, allowing to analyse the environment.



The wireless transmitter is equipped with a DMX input and output, on XLR 5 pins. Its two antennas allow a 300m range wifi connection. Connect the transmitter to L'APPS, INNLED's mobile application and easily control all your lights.

# TECHNICAL SPECIFICITIES

## POWER SUPPLY

- By USB port
- DC USB 5V

## HF POWER

- (2,4Ghz) : 20db (100mW)

## FREQUENCIES

- 21

## UNIVERSES AND DMX CHANNELS

- 31
- 15872 channels

## ANTENNA

- 1db articulated external
- SMA connector

## INPUTS

- USB "OPEN DMX" input
- 5 point XLR DMX input
- 1 Art Net universe on the access point input

## OUTPUT

- 5 point reboosted XLR output

## SECURITY

- SSID and wifi password predefined choice
- WPA2 security on Wifi

## PROTOCOL

- W2.4EC-DMX-A ET B

## IP CLASS

- IP20

## NORM

- CE

## DIMENSIONS

- L 100 x l 85 x H 48mm

## WEIGHT

- +/- 300g

## TEMPERATURE RANGE

- 0° to +40°C

## WARRANTY

- 2 years

